

**Equipment Configuration Checklist Integrated with FDR OMAHA (credit/debit)**

	<u>Paper Check w/o Chk Rdr</u>	<u>Paper Check w/ Chk Rdr</u>	<u>Check Conversion w/ Imager (guar only)</u>	<u>Check Conversion w/ Chk Rdr (verify only)</u>	<u>Gift Card</u>	<u>Loyalty</u>	<u>Comments:</u>
<b>Lipman: Nurit 2085 / 2085+ / 3000 / 3020</b>	Yes	Magtek Mini MICR	EC5003 / EC5004 EC6004 / EC6005 EC6004/EC6005f EC6014/EC6014f	Magtek Mini MICR	Yes	Yes	NOS 7 upgrade, unless paper check. 3000 model can not upgrade to NOS 7; only paper check or stand alone. Credit Card support downgraded to Class B. Looses ability to auto settle any batches. Franking option available with the RDM EC6004/EC6005/EC6014f.
<b>Lipman: Nurit 3010 / 8000</b>	Yes	Magtek Mini MICR	EC5003 / EC5004 EC6004 / EC6005 EC6004/EC6005f EC6014/EC6014f	Magtek Mini MICR	Yes	Yes	Same as above... Only models 10 and 12 of the 3010 can be upgraded to NOS 7. Nurit 8000 does not have ability to connect a check reader/imager, unless connected to base. Must have a physical analog telephone connection. Franking option available with the RDM EC6004/EC6005/EC6014f.
<b>Lipman: Nurit 8320 / 8400</b>	Yes	Magtek Mini MICR	EC5003 / EC5004 EC6004 / EC6005 EC6004/EC6005f EC6014/EC6014f	Magtek Mini MICR	Yes	Yes	Credit Card support downgraded to Class B. Looses ability to auto settle any batches. Franking option available with the RDM EC6004/EC6005/EC6014f. 8320 Model 14A is a proprietary terminal, SPS cannot load it, the acquirer must add SPS.
<b>Verifone: Omni 3200</b>	Yes	Magtek Mini MICR	No	No	No	No	
<b>Verifone: Omni 3730 (Vx510) / 3740 / 3750</b>	Yes	Yes Magtek Mini MICR CR600	Yes EC5003 / EC5004 EC6004 / EC6005 EC6004/EC6005f EC6014/EC6014f CR1000 Magtek MICR Imager	Yes Magtek Mini MICR CR600	Yes	Yes	3730 model does not support dual comm (IP) & can only accommodate 2 applications. If integrating credit, debit, check and gift/loyalty, terminal must be 4 MEG (minimum). IP or Dual Comm needed if loading an IP Application. Franking option available with the RDM EC6004/EC6005/EC6014f. If using the Magtek MICR Imager it must be ordered with 19200 bps.
<b>Verifone: Vx570 / Vx610 / Vx510 (Omni 3730)</b>	Yes	Yes Magtek Mini MICR CR600	Yes EC5003 / EC5004 EC6004 / EC6005 EC6004/EC6005f EC6014/EC6014f CR1000 Magtek MICR Imager	Yes Magtek Mini MICR CR600	Yes	Yes	Vx510 model does not support dual comm (IP) & can only accommodate 2 applications. If integrating credit, debit, check and gift/loyalty, terminal must be 4 MEG (minimum). IP or Dual Comm needed if loading an IP Application. Franking option available with the RDM EC6004/EC6005/EC6014f. Vx610 must have physical analog phone or IP connection. If using the Magtek MICR imager it must be ordered with 19200 bps.
<b>Verifone: Tranz 3307 / 3807 / 460</b>	Yes	Magtek Mini MICR	No	No	No	No	
<b>Verifone: Tranz 380x2</b>	Yes	Magtek Mini MICR	EC5003 / EC5004 EC6004 / EC6005 EC6004/EC6005f EC6014/EC6014f	Magtek Mini MICR	Yes	No	Franking option available with the RDM EC6004/EC6005/EC6014f.
<b>Ingenico: Elite 510 / 512 / 710 / 712</b>	See Comments	See Comments encheck 2500	See Comments encheck 2600	See Comments encheck 2500	See Comments	No	<i>If a proprietary credit card app., the cc comp. must provide the terminal password in order to download any SPS app.</i>
<b>TechTrex: PrimeTrex</b>	Yes	Yes Magtek Mini MICR	Yes EC5003 / EC5004 EC6004 / EC6005 EC6004/EC6005f EC6014/EC6014f	Yes Magtek Mini MICR	Yes	Yes	Franking option available with the RDM EC6004/EC6005/EC6014f. ConverTrex needed if using IP with a PrimeTrex.
<b>TechTrex: PrimeTrex IP ("PAI-Trex")</b>	Yes	Yes Magtek Mini MICR	Yes EC5003 / EC5004 EC6004 / EC6005 EC6004/EC6005f EC6014/EC6014f	Yes Magtek Mini MICR	Yes	Yes	Franking option available with the RDM EC6004/EC6005/EC6014f. PrimeTrex IP and PAI Trex do not need ConverTrex for IP
<b>Hypercom: T4100 / T4205 / T4210 / T4220</b>	Yes	Yes Magtek Mini MICR	Yes EC5003 / EC5004 EC6004 / EC6005 EC6004/EC6005f EC6014/EC6014f Magtek MICR Imager	Yes Magtek Mini MICR	Yes	Yes	Franking option available with the RDM EC6004/EC6005/EC6014f. T4205 and T4210 are dial-up only
<b>Hypercom: T7p / T77 / Plus</b>	Yes	Magtek Mini MICR	EC5003 / EC5004 EC6004 / EC6005 EC6004/EC6005f EC6014/EC6014f Magtek MICR Image (see comments)	Magtek Mini MICR	Yes	No	Requires SPOS09 software and acquirer willing to add SPS. SPS can build a dnlid file if provided VAR for other services. Franking option available with the RDM EC6004/EC6005/EC6014f. Must be 512K or higher. If using the Magtek MICR Imager it must be ordered with 9600 bps.
<b>Hypercom: ICE 5500</b>	Yes	Magtek Mini MICR	EC5003 / EC5004 EC6004 / EC6005 EC6004/EC6005f EC6014/EC6014f Magtek MICR Image (see comments)	Magtek Mini MICR	Yes	No	Requires SPOS09 software and acquirer willing to add SPS. SPS can build a dnlid file if provided VAR for other services. Franking option available with the RDM EC6004/EC6005/EC6014f. Must be 512K or higher. If using the Magtek MICR Imager it must be ordered with 9600 bps.
<b>Hypercom: ICE 5700</b>	No	Yes (integrated)	No	Yes (integrated)	Yes	No	Requires SPOS09 software and acquirer willing to add SPS. SPS can build a dnlid file if provided VAR for other services. Must be 512K or higher.

(last updated 9/3/09)