

**Equipment Configuration Checklist Integrated with GLOBAL (credit/debit)**

	<u>Paper Check w/o Chk Rdr</u>	<u>Paper Check w/ Chk Rdr</u>	<u>Check Conversion w/ Imager (guar only)</u>	<u>Check Conversion w/ Chk Rdr (verify only)</u>	<u>Gift Card</u>	<u>Loyalty</u>	<u>Comments:</u>
<b>Lipman: Nurit 2085 / 2085+ / 3000 / 3020</b>	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014f/EC6014f	Magtek Mini MICR	Yes	Yes	NOS 7 upgrade, unless paper check. 3000 model can not upgrade to NOS 7; only paper check or stand alone. Credit Card support downgraded to Class B. Loses ability to auto settle. Franking option available with the RDM EC6004f/EC6005f/EC6014f.
<b>Lipman: Nurit 3010 / 8000</b>	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014f/EC6014f	Magtek Mini MICR	Yes	Yes	Same as above... Only models 10 and 12 of the 3010 can be upgraded to NOS 7. Nurit 8000 does not have ability to connect a check reader/imager, unless connected to base. Must have an physical analog telephone connection. Franking option available with the RDM EC6004f/EC6005f/EC6014f.
<b>Lipman: 8320 / 8400</b>	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014f/EC6014f	Magtek Mini MICR	Yes	Yes	Credit Card support downgraded to Class B. Loses ability to auto settle. Franking option available with the RDM EC6004f/EC6005f/EC6014f. 8320 Model 14A is a proprietary terminal, SPS cannot load it, the acquirer must add SPS.
<b>Verifone: Omni 3200</b>	Yes	Magtek Mini MICR	No	No	No	No	
<b>Verifone: Omni 3730 (Vx510) / 3740 / 3750</b>	Yes	Yes Magtek Mini MICR CR600	Yes EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014f/EC6014f CR1000 Magtek MICR Imager	Yes Magtek Mini MICR CR600	Yes	Yes	3730 model does not support dual comm (IP) & can only accommodate 2 applications. If integrating credit, debit, check and gift/loyalty, terminal must be 4 MEG (minimum). IP or Dual Comm needed if loading an IP Application. Franking option available with the RDM EC6004f/EC6005f/EC6014f. If using the Magtek MICR Imager it must be ordered with 19200 bps.
<b>Verifone: Vx570 / Vx610 / Vx510 (Omni 3730)</b>	Yes	Yes Magtek Mini MICR CR600	Yes EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014f/EC6014f CR1000 Magtek MICR Imager	Yes Magtek Mini MICR CR600	Yes	Yes	Vx510 model does not support dual comm (IP) & can only accommodate 2 applications. If integrating credit, debit, check and gift/loyalty, terminal must be 4 MEG (minimum). IP or Dual Comm needed if loading an IP Application. Franking option available with the RDM EC6004f/EC6005f/EC6014f. Vx610 must have physical analog phone or IP connection. If using the Magtek MICR Imager it must be ordered with 19200 bps.
<b>Verifone: Tranz 3307 3807 460</b>	Yes	Magtek Mini MICR	No	No	No	No	See Stand Alone SPS checklist for conversion and gift possibilities.
<b>Verifone: Tranz 380x2</b>	Yes	Magtek Mini MICR	EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014f/EC6014f	Magtek Mini MICR	Yes	No	Franking option available with the RDM EC6004f/EC6005f/EC6014f.
<b>Ingenico: Elite 510 / 512 / 710 / 712</b>	See Comments	See Comments encheck 2500	See Comments encheck 2600	See Comments encheck 2500	See Comments	No	If a proprietary credit card app., the cc comp. must provide the terminal password in order to download any SPS app.
<b>TechTrex: PrimeTrex</b>	Yes	Yes Magtek Mini MICR	Yes EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014f/EC6014f	Yes Magtek Mini MICR	Yes	Yes	Franking option available with the RDM EC6004f/EC6005f/EC6014f. ConverTrex needed if using IP with a PrimeTrex.
<b>TechTrex: PrimeTrex IP ("PAI-Trex")</b>	Yes	Yes Magtek Mini MICR	Yes EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014f/EC6014f	Yes Magtek Mini MICR	Yes	Yes	Franking option available with the RDM EC6004f/EC6005f/EC6014f. PrimeTrex IP and PAI Trex do not need ConverTrex for IP
<b>Hypercom: T4100 / T4205 / T4210 / T4220</b>	Yes	Yes Magtek Mini MICR	Yes EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014f/EC6014f Magtek MICR Imager	Yes Magtek Mini MICR	Yes	Yes	Franking option available with the RDM EC6004f/EC6005f/EC6014f. T4205 and T4210 are dial-up only
<b>Hypercom: T7p / T77 / Plus</b>	See Comments	See Comments Magtek Mini MICR	See Comments EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014f/EC6014f Magtek MICR Image	See Comments Magtek Mini MICR	See Comments	No	Requires SPOS09 software and acquirer willing to add SPS. SPS can build a dnl file if provided VAR for other services. Franking option available with the RDM EC6004f/EC6005f/EC6014f. Must be 512K or higher. If using the Magtek MICR Imager it must be ordered with 9600 bps.
<b>Hypercom: ICE 5500</b>	See Comments	See Comments Magtek Mini MICR	See Comments EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014f/EC6014f Magtek MICR Image	See Comments Magtek Mini MICR	See Comments	No	Requires SPOS09 software and acquirer willing to add SPS. SPS can build a dnl file if provided VAR for other services. Franking option available with the RDM EC6004f/EC6005f/EC6014f. Must be 512K or higher. If using the Magtek MICR Imager it must be ordered with 9600 bps.
<b>Hypercom: ICE 5700</b>	No	See Comments (integrated)	No	See Comments (integrated)	See Comments	No	Requires SPOS09 software and acquirer willing to add SPS. SPS can build a dnl file if provided VAR for other services. Must be 512K or higher.

(last updated 9/3/09)