

Equipment Configuration Checklist Integrated with MAPP (credit/debit)

| | <u>Paper Check w/o Chk Rdr</u> | <u>Paper Check w/ Chk Rdr</u> | <u>Check Conversion w/ Imager (quar only)</u> | <u>Check Conversion w/ Chk Rdr (verify only)</u> | <u>Gift Card</u> | <u>Loyalty</u> | <u>Comments:</u> |
|--|------------------------------------|------------------------------------|--|--|------------------|----------------|---|
| Lipman: Nurit 2085 / 2085+ / 3000 / 3020 | Yes | Magtek Mini MICR | EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014i/EC6014f | Magtek Mini MICR | Yes | Yes | NOS 7 upgrade, unless paper check. 3000 model can not upgrade to NOS 7; only paper check or stand alone. Credit Card support downgraded to Class B. Loses ability to auto settle. Franking option available with the RDM EC6004f/EC6005f/EC6014f. |
| Lipman: Nurit 3010 / 8000 | Yes | Magtek Mini MICR | EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014i/EC6014f | Magtek Mini MICR | Yes | Yes | Same as above... Only models 10 and 12 of the 3010 can be upgraded to NOS 7. Nurit 8000 does not have ability to connect a check reader/imager, unless connected to base. Must have a physical analog telephone connection. Franking option available with the RDM EC6004f/EC6005f/EC6014f. |
| Lipman: 8320 / 8400 | Yes | Magtek Mini MICR | EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014i/EC6014f | Magtek Mini MICR | Yes | Yes | Credit Card support downgraded to Class B. Loses ability to auto settle. Franking option available with the RDM EC6004f/EC6005f/EC6014f. 8320 Model 14A is a proprietary terminal, SPS cannot load it, the acquirer must add SPS. |
| Thales: Talento | Yes | Magtek Mini MICR | No | No | No | No | |
| Verifone: Omni 3200 | Yes | Magtek Mini MICR | No | No | No | No | |
| Verifone: Omni 3730 (Vx510) / 3740 / 3750 | Yes | Yes Magtek Mini MICR CR600 | Yes EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014i/EC6014f CR1000 Magtek MICR Imager | Yes Magtek Mini MICR CR600 | Yes | Yes | 3730 model does not support dual comm (IP) & can only accommodate 2 applications. If integrating credit, debit, check and gift/loyalty, terminal must be 4 MEG (minimum). IP or Dual Comm needed if loading an IP Application. Franking option available with the RDM EC6004f/EC6005f/EC6014f. If using the Magtek MICR Imager it must be ordered with 19200 bps. |
| Verifone: Vx570 / Vx610 / Vx510 (Omni 3730) | Yes | Yes Magtek Mini MICR CR600 | Yes EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014i/EC6014f CR1000 Magtek MICR Imager | Yes Magtek Mini MICR CR600 | Yes | Yes | Vx510 model does not support dual comm (IP) & can only accommodate 2 applications. If integrating credit, debit, check and gift/loyalty, terminal must be 4 MEG (minimum). IP or Dual Comm needed if loading an IP Application. Franking option available with the RDM EC6004f/EC6005f/EC6014f. Vx610 must have physical analog phone or IP connection. If using the Magtek MICR Imager it must be ordered with 19200 bps. |
| Verifone: Tranz 330 / 380 / 460 | Yes | Magtek Mini MICR | No | No | No | No | See Stand Alone SPS checklist for conversion and gift possibilities. |
| Verifone: Tranz 380x2 | Yes | Magtek Mini MICR | EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014i/EC6014f | Magtek Mini MICR | Yes | No | Franking option available with the RDM EC6004f/EC6005f/EC6014f. |
| Ingenico: Elite 510 / 512 / 710 / 712 | See Comments | See Comments encheck 2500 | See Comments encheck 2600 | See Comments encheck 2500 | See Comments | No | If a proprietary credit card app., the cc comp. must provide the terminal password in order to download any SPS app. |
| TechTrex: PrimeTrex | Yes | Yes Magtek Mini MICR | Yes EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014i/EC6014f | Yes Magtek Mini MICR | Yes | Yes | Franking option available with the RDM EC6004f/EC6005f/EC6014f. ConverTrex needed if using IP with a PrimeTrex. |
| TechTrex: PrimeTrex IP ("PAI-Trex") | Yes | Yes Magtek Mini MICR | Yes EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014i/EC6014f | Yes Magtek Mini MICR | Yes | Yes | Franking option available with the RDM EC6004f/EC6005f/EC6014f. PrimeTrex IP and PAI Trex do not need ConverTrex for IP |
| Hypercom: T4100 / T4205 / T4210 / T4220 | Yes | Yes Magtek Mini MICR | Yes EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014i/EC6014f Magtek MICR Imager | Yes Magtek Mini MICR | Yes | Yes | Franking option available with the RDM EC6004f/EC6005f/EC6014f. T4205 and T4210 are Dial-up only |
| Hypercom: T7p / T77 / Plus | See Comments | See Comments Magtek Mini MICR | See Comments EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014i/EC6014f Magtek MICR Imager (see comments) | See Comments Magtek Mini MICR | See Comments | No | Requires SPOS09 software and acquirer willing to add SPS. Franking option available with the RDM EC6004f/EC6005f/EC6014f. Must be 512K or higher. If using the Magtek MICR Imager it must be ordered with 9600 bps. |
| Hypercom: ICE 5500 | See Comments | See Comments Magtek Mini MICR | See Comments EC5003i / EC5004i EC6004i / EC6005i EC6004f/EC6005f EC6014i/EC6014f Magtek MICR Imager (see comments) | See Comments Magtek Mini MICR | See Comments | No | Requires SPOS09 software and acquirer willing to add SPS. Franking option available with the RDM EC6004f/EC6005f/EC6014f. Must be 512K or higher. If using the Magtek MICR Imager it must be ordered with 9600 bps. |
| Hypercom: ICE 5700 | No | See Comments chk rdr integrated | No | See Comments chk rdr integrated | See Comments | No | Requires SPOS09 software and acquirer willing to add SPS. Must be 512K or higher. |

(last updated 9/3/09)